

<p>1</p> <p>2</p> <p>3</p> <p>4</p> <p>5</p> <p>6</p> <p>7</p> <p>8</p>	<p>1. GRAY OR Y-G STN. TRANSPARENT LCD; Y-G BACKLIGHT; 6 O'CLOCK OR 12 O'CLOCK;</p> <p>2. FSTN. TRANSPARENT LCD; WHITE BACKLIGHT; 6 O'CLOCK OR 12 O'CLOCK;</p> <p>3. GRAY STN. TRANSPARENT LCD; WHITE BACKLIGHT; 6 O'CLOCK;</p> <p>4. Y-G STN. TRANSPARENT LCD; Y-G BACKLIGHT; 6 O'CLOCK;</p> <p>5. BLUE STN. TRANSPARENT LCD; WHITE BACKLIGHT; 6 O'CLOCK;</p> <p>6. GRAY OR Y-G STN. REFLECTIVE LCD; WITHOUT BACKLIGHT; 6 O'CLOCK OR 12 O'CLOCK;</p>	<p>THE PART NUMBER IN MASS PRODUCTION</p> <p>UNIT: MM</p> <p>3RD ANGLE</p> <p>SCALE: 1:1</p> <p>DRAWN: _____</p> <p>CHECKED: _____</p> <p>APPROVED: _____</p> <p>TITLE: LCM</p> <p>MODEL NO: ACM1602K SERIES</p> <p>PART NO: _____</p> <p>REV: A</p> <p>SH NO: 1/1</p>									
<p>A</p> <p>B</p> <p>C</p> <p>D</p> <p>E</p> <p>F</p>		<table border="1"> <tr> <th>ITEM</th> <th>T1</th> <th>T2</th> </tr> <tr> <td>BACKLIGHT</td> <td>10.2</td> <td>13.0</td> </tr> <tr> <td>WITHOUT BL</td> <td>6.2</td> <td>9.0</td> </tr> </table>	ITEM	T1	T2	BACKLIGHT	10.2	13.0	WITHOUT BL	6.2	9.0
ITEM	T1	T2									
BACKLIGHT	10.2	13.0									
WITHOUT BL	6.2	9.0									
<p>1</p> <p>2</p> <p>3</p> <p>4</p> <p>5</p> <p>6</p> <p>7</p> <p>8</p>	<p>1. VSS</p> <p>2. VDD</p> <p>3. VO</p> <p>4. RS</p> <p>5. R/W</p> <p>6. E</p> <p>7. DB0</p> <p>8. DB1</p> <p>9. DB2</p> <p>10. DB3</p> <p>11. DB4</p> <p>12. DB5</p> <p>13. DB6</p> <p>14. DB7</p> <p>+</p> <p>BL-</p> <p>BL+</p>	<p>OPERATING VOLTAGE: 5V</p> <p>LCD DRIVING VOLTAGE: 4.5V</p> <p>LCD DRIVE METHOD: 1/16 DUTY 1/5 BIAS</p> <p>LCD DRIVE IC: SPLC780D-001 OR EQUIV</p> <p>NOTE:</p> <p>1. The backlight can be driven by pin +, pin - or pin1, pin2 which is selectable.</p> <p>2. The voltage of backlight is depended on the backlight color and the value of current-limiting resistance.</p> <p>3. The operating voltage can be driven by 3.3v which is selectable.</p>									
<p>1</p> <p>2</p> <p>3</p> <p>4</p> <p>5</p> <p>6</p> <p>7</p> <p>8</p>	<p>U1</p> <p>SEG1-80</p> <p>COM1-16</p> <p>COM1</p> <p>COM16</p> <p>LED BACKLIGHT</p> <p>SEG1---SEG80</p> <p>COM1</p> <p>COM16</p> <p>LCD 16X2</p>	<p>ITEM</p> <p>SELECTABLE CONTENTS</p> <p>STN YELLOW MODE</p> <p>STN GRAY MODE</p> <p>STN BLUE MODE</p> <p>FSTN</p> <p>REFLECTIVE</p> <p>TRANSPARENT</p> <p>TRANSMISSIVE, POSITIVE</p> <p>TRANSMISSIVE, NEGATIVE</p> <p>VIEWING DIRECTION</p> <p>6 O'CLOCK</p> <p>12 O'CLOCK</p> <p>WHITE</p> <p>Y-G</p> <p>RED</p> <p>GREEN</p> <p>BLUE</p> <p>AMBER</p> <p>TRI-COLOR</p> <p>TEMPERATURE RANGE</p> <p>STANDARD TEMPERATURE</p> <p>WIDE TEMPERATURE</p> <p>CHARACTER PATTERNS</p> <p>ENGLISH-JAPANESE FONTS</p> <p>ENGLISH-EUROPEAN FONTS</p> <p>ENGLISH-RUSSIAN FONTS</p> <p>CYRILLIC FONTS</p> <p>HEBREW FONTS</p>									
<p>1</p> <p>2</p> <p>3</p> <p>4</p> <p>5</p> <p>6</p> <p>7</p> <p>8</p>	<p>DISP LAY PATTEN</p>	<p>ITEM</p> <p>SELECTABLE CONTENTS</p> <p>STN YELLOW MODE</p> <p>STN GRAY MODE</p> <p>STN BLUE MODE</p> <p>FSTN</p> <p>REFLECTIVE</p> <p>TRANSPARENT</p> <p>TRANSMISSIVE, POSITIVE</p> <p>TRANSMISSIVE, NEGATIVE</p> <p>VIEWING DIRECTION</p> <p>6 O'CLOCK</p> <p>12 O'CLOCK</p> <p>WHITE</p> <p>Y-G</p> <p>RED</p> <p>GREEN</p> <p>BLUE</p> <p>AMBER</p> <p>TRI-COLOR</p> <p>TEMPERATURE RANGE</p> <p>STANDARD TEMPERATURE</p> <p>WIDE TEMPERATURE</p> <p>CHARACTER PATTERNS</p> <p>ENGLISH-JAPANESE FONTS</p> <p>ENGLISH-EUROPEAN FONTS</p> <p>ENGLISH-RUSSIAN FONTS</p> <p>CYRILLIC FONTS</p> <p>HEBREW FONTS</p>									
<p>1</p> <p>2</p> <p>3</p> <p>4</p> <p>5</p> <p>6</p> <p>7</p> <p>8</p>	<p>DISPLAYTRONIC</p> <p>XIAMEN ZETTLER ELECTRONICS CO., LTD.</p>										